

Date

Name

Client

Project Name


Quote#

Type/Quantity

MINI DIRO R 83020

415 132 832

[Weblink](#)



Cutout shape/size: 67 mm

Recessed depth: 70 mm

Thickness of mounting surface: min.5

Available colors: BLACK (415 132 832 B)
WHITE (415 132 832 W)

FIXED

INCL.1 x POWERLED WHITE 4,1-6W / CRI>80 / 3000K / max.475lm

INCL.1 x LENS FL-20°

EXCL.LED POWER SUPPLY 350-500mA-DC

ON REQUEST : 4000K

LED Technics: Light source: 475 lm // 6 W // 80 lm/W
Luminaire: 7 W // 0 lm/W

Class: III

Weight: 0.3 KG

Protection level: IP20

Minimum distance: n.a.

Options: LED POWER SUPPLY 350 / 500mA-DC DIM













For detailed installation instructions, please consult the manual. [415 132 XXX HAND.pdf](#)

MINI DIRO R 83020


415 132 832

Related references

LED POWER SUPPLIES

<p>Weblink / Specs sheet</p>  <p>LED POWER CONVERTOR 24V -> 350mA / 15W 300 2415 350 Number of luminaires: 3</p>	<p>Weblink / Specs sheet</p>  <p>LED POWER SUPPLY 350mA-DC / 15W 300 90 91 100-240V / 50-60Hz Number of luminaires: 3(2)</p>	<p>Weblink / Specs sheet</p>  <p>LED POWER SUPPLY 350mA-DC / 16W DIM8 300 90 3112 110-240V / 50-60Hz Number of luminaires: 2 -> 3</p>	<p>Weblink / Specs sheet</p>  <p>LED POWER SUPPLY 350mA-DC / 17W 300 90 913 100-240V / 50-60Hz Number of luminaires: 3(2)</p>
<p>Weblink / Specs sheet</p>  <p>LED POWER SUPPLY 350mA-DC / 18W DIM8 300 90 116 220-240V / 50-60Hz Number of luminaires: min.3 - max.3</p>	<p>Weblink / Specs sheet</p>  <p>LED POWER SUPPLY 350mA-DC / 8W 300 90 108 100-240V / 50-60Hz Number of luminaires: 1</p>	<p>Weblink / Specs sheet</p>  <p>LED POWER SUPPLY 500mA-DC / 20W 300 90 92 110-240V / 50-60Hz Number of luminaires: 3(1)</p>	<p>Weblink / Specs sheet</p>  <p>LED POWER SUPPLY 500mA-DC / 20W DIM8 300 90 117 220-240V / 50-60Hz Number of luminaires: 2 -> 3</p>
<p>Weblink / Specs sheet</p>  <p>LED POWER SUPPLY 500mA-DC / 32W DIM8 300 90 5120 110-240V / 50-60Hz Number of luminaires: 2 -> 3</p>	<p>Weblink / Specs sheet</p>  <p>LED POWER SUPPLY MULTI-POWER 300 90 914 110-240V / 50-60Hz Number of luminaires: 5 / 5 / - / - / -</p>	<p>Weblink / Specs sheet</p>  <p>LED POWER SUPPLY MULTI-POWER DIM1 300 90 64 120-240V / 50-60Hz Number of luminaires: 4(3) / 3(2) / -</p>	<p>Weblink / Specs sheet</p>  <p>LED POWER SUPPLY MULTI-POWER DIM5 300 90 68 110-240V / 50-60Hz Number of luminaires: 3 / 3(2) / - / -</p>

[Weblink / Specs sheet](#)




LED POWER SUPPLY MULTI-
POWER DIM6
300 90 61

220-240V / 50-60Hz

Number of luminaires: 3 / 3(2) / -

[Weblink / Specs sheet](#)




LED POWER SUPPLY MULTI-
POWER DIM7
300 90 60

110-240V / 50-60Hz

Number of luminaires: 3 / 3(2) / -

[Weblink / Specs sheet](#)



LED POWER SUPPLY MULTI-
POWER DIM9
300 90 63


120-240V / 50-60Hz

Number of luminaires: 5 / 5 / - / - / -

Related references

CONTROL GEAR, BALLAST AND TRANSFORMERS

[Weblink / Specs sheet](#)



LED POWER CONVERTOR
24V-DC TO MULTI CURRENT
48W DIM9
300 90 67

Number of luminaires: 3